

CDMA800 / CDMA1900 COMBINER

Model : PW-DUP-8033

1、 Part Number : PW-DUP-8033

2、 Product Name : Dual-band Combiner

	CH1	CH2
Frequency range (MHz)	825~890	1880-1990
Band-width (MHz)	65	110
Insertion loss (dB)	≤ 0.6	≤ 0.6
Ripple in-band (dB)	≤ 0.4	≤ 0.4
Rejection (dB)	≥80 @CH2	≥80 @CH1
Isolation (dB)	≥80 @CH2	≥80 @CH1
Return loss (dB)	≥ 18	
Impedance (Ω)	50	
PIM (dBc)	≤-140@ 2 x +43dBm	
Connector	N-Female or DIN-Female	
Power rating (W)	100	
Temperature (°C)	0 to +65	
Size (mm) *	158×88×50	
Weight (kg) *	2	

*Manufacturer has the right to change Size & Weight (if needed)

3、 Product Picture :

